

B & R Automation - System 2010 Controllers

2UM900.6



 **In Stock, Ships in 3-5 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **2UM900.6** is a part of the **System 2010 Controllers Series** by **B & R Automation**.

Specifications

Analog input conversion time:	21 ms	Analog input resolution:	12-bit	Analog inputs:	4 channels (±10 V or 0 to 20 mA)
Analog output resolutions:	12-bit (voltage), 11-bit (current)	Analog outputs:	2 channels (±10 V & 0 to 20 mA)	Base plate module compatibility:	BP200, BP201, BP210
Digital input max voltage:	30 VDC	Digital input nominal voltage:	24 VDC	Digital input resistance:	4 kΩ
Digital inputs:	8 channels (2×4)	Digital output continuous current:	0.5 A	Digital output supply voltage:	24 VDC
Digital output switching voltages:	18 to 30 VDC (nom. 24 VDC)	Digital outputs:	8 transistor channels	Dimensions (H×W×D):	285×40×185 mm
Last Verified:	08/13/2025 4:23 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.