

Bosch Rexroth Indramat - MAF Induction Motor Series

MAF100C-0250-FR-C0-AK0-05-R1



 [Request a Quote](#)

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **MAF100C-0250-FR-C0-AK0-05-R1** is a part of the **MAF Induction Motor Series** by **Bosch Rexroth Indramat**.

Specifications

Rated power:	16.23 kW	Rated speed:	2500 1/min	Maximum torque:	138.1 Nm
Maximum current:	85.8 A	Maximum speed with bearing H:	11000 1/min	Continuous current at standstill:	38.5 A
Thermal time constant:	3.5 min	Discharge capacity:	9.4 nF	Power wire cross-section:	10 mm ²
Rotor moment of inertia:	0.0284 kg * m ²	Last Verified:	11/21/2024 4:41 PM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.