



Bosch Rexroth Indramat - VT 3000 Analog Amplifiers

VT 3013-36



[Request a Quote](#)

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 3013-36** is a part of the **VT 3000 Analog Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Command Output Level:	0-6 V across test point BU1	Input Control Voltage:	± 9 V	Input Signal Range:	±10 V
Maximum Output Current:	800 mA	Maximum Output Load:	R 19.5 ?	Minimum Input Load:	? 500 ?
Minimum Output (bias) Current:	20 mA	Overload Protection:	Integrated short-circuit and thermal overload protection	Power Requirements:	30 W
Power Supply Voltage:	24 VDC ±10%	Pulse Frequency:	160 to 180 Hz	Space Requirements:	1 div. = 5.08 mm; Face plate requirement: 8 divisions
Temperature Drift:	0.5% (from I _{max})/K	Test Points:	BU2 and BU3 (measurement scale: 1 mV = 1 mA)	Weight:	0.33 lb (0.15 kg)
Last Verified:	07/02/2025 6:08 AM				

Contact Us

1620 Old Apex Road, Cary, NC 27513, USA

Toll Free: [1-888-551-3082](tel:1-888-551-3082)

International: [1-919-443-0207](tel:1-919-443-0207)

Fax: [1-919-867-6204](tel:1-919-867-6204)

Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.