



Bosch Rexroth Indramat - VT 3000 Analog Amplifiers

VT 3013-37



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 3013-37** is a part of the **VT 3000 Analog Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Differential Analog Input:	Accepts 0 to 10 V difference between pins 16a and 16c	Fuse Rating:	2.5 Ampere (5 mm x 20 mm)	Input Control Voltage:	±9 V
Maximum Output Current:	800 mA	Maximum Output Load:	19.5 ? (coil resistance)	Minimum Input Load:	? 500 ?
Minimum Output (bias) Current:	20 mA	Power Requirements:	30 W	Power Supply Voltage:	24 VDC ±10%
Pulse Frequency:	160 to 180 Hz	Space Requirements:	1 division = 0.200 inches (5.08 mm) per TE (1 HP)	Temperature Drift:	0.5% per K (from I _{max})
Test Point Specifications:	BU2 and BU3 measure output signals from 20 mA to 800 mA	Weight:	0.33 lb (0.15 kg)	Last Verified:	07/04/2025 3:18 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.