



Bosch Rexroth Indramat - VT 3000 Analog Amplifiers

VT 3018 S38



 **In Stock, Ships 2-3 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 3018 S38** is a part of the **VT 3000 Analog Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Certifications:	UL 508, CE certified	Connection Interface:	Plug-in terminals	Height:	4.2 in (107 mm)
Input Control Voltage:	±9 V	Max Output Current:	800 mA	Max Output Load Resistance:	19.5 ?
Min Input Load Resistance:	?500 ?	Min Output Bias Current:	20 mA	Power Consumption:	30 W
Power Supply Voltage:	24 VDC ±10%	Pulse Frequency:	160SPR180 Hz	Temperature Drift:	0.5%/K (of I _{max})
	20SPR800 mA		Output signal for solenoid A	Vibration Resistance:	Up to 5 g, 10SPR150 Hz
Test Point BU2:	output for solenoid B	Test Point BU3:		Last Verified:	07/02/2025 10:02 AM
Weight:	0.33 lb (0.15 kg)	Width:	7.28 in (185 mm)		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.