

Bosch Rexroth Indramat - VT 3000 Analog Amplifiers

VT 3024-36a



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 3024-36a** is a part of the **VT 3000 Analog Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Fuse Rating:	2.5 Ampere (5 mm x 20 mm fuse)	Input Control Voltage:	± 9 V	Maximum Output Current:	800 mA
Maximum Output Load:	19.5 ?	Minimum Input Load:	? 500 ?	Minimum Output (bias) Current:	20 mA
Power Requirements:	30 W	Power Supply Voltage:	24 VDC ±10%	Pulse Frequency:	160 to 180 Hz
Temperature Drift:	0.5% (from I _{max})/K	Test Point Bu2:	Output signal for solenoid B; 20-800 mA	Test Point Bu3:	Output signal for solenoid A; 20-800 mA
Weight:	0.33 lb (0.15 kg)	Last Verified:	07/01/2025 8:14 PM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.