



Bosch Rexroth Indramat - VT 3000 Analog Amplifiers

VT 3024S35



 **In Stock, Ships 2-3 Days**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 3024S35** is a part of the **VT 3000 Analog Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Fuse dimension:	5 mm × 20 mm	Fuse rating:	2.5 A	Input control voltage:	±9 V
Maximum output current:	800 mA	Maximum output load:	19.5 ?	Minimum input load:	?500 ?
Minimum output bias current:	20 mA	Power requirement:	30 W	Power supply voltage:	24 VDC ±10%
Pulse frequency:	160 to 180 Hz	Temperature drift:	0.5%/K (from I _{max})	Test point BU2:	Solenoid B current range: 20 ^{SPB} 800 mA
Test point BU3:	Solenoid A current range: 20 ^{SPA} 800 mA	Weight:	0.33 lb (0.15 kg)	Last Verified:	07/03/2025 8:49 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

