

## Bosch Rexroth Indramat - VT-5000 IO Cards

### VT 4593-36 A



 [Request a Quote](#)

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout






Free Ground  
Shipping



One Year  
Warranty

The **VT 4593-36 A** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

### Specifications

<b>Card Dimensions:</b>	Euro-card 100 x 160 mm (DIN 41494)	<b>Clock Frequency:</b>	Self-clocking up to approx. 1.5 kHz	<b>Command Socket Voltage  w:</b>	0 to ±6 V (Ri = 100 ?)
<b>Connector:</b>	32-pin male DIN 41612 form D	<b>Current Consumption:</b>	< 2 A	<b>Fuse Rating:</b>	2.5 A T
<b>Inductive Transducer Load Capacity:</b>	30 mA per output	<b>Inductive Transducer Output Voltage:</b>	5 V amplitude per output	<b>Nominal Operating Voltage:</b>	24 V DC (+40%/? 10%)
<b>Operating Voltage Range:</b>	22 V  35 V	<b>Oscillator Frequency:</b>	2.5 kHz ±10%	<b>Position Socket Voltage  x:</b>	0 to 6 V (Ri = 100 ?)
<b>Power Consumption:</b>	< 50 VA	<b>Ramp Time Adjustment:</b>	30 ms to 1 s or 5 s (±20%)	<b>Regulated Voltage Output:</b>	±9 V ±1% (? ±25 mA load)
<b>VT5005 Solenoid Current:</b>	Imax 1.8 A (±20%, R20=5.4 ?)	<b>VT5006 Solenoid Current:</b>	Imax 2.2 A (±20%, R20=10 ?)	<b>Last Verified:</b>	07/11/2025 5:32 PM

### Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

### Shipping Options



### Payment Methods

