

#### **Bosch Rexroth Indramat - VT-5000 IO Cards**

VT 5006 S13



# 🗈 In Stock, Shipping Varies

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- ☑ Up to half the cost of the manufacturer



Grour



Secure Online Checkout Free Ground Shipping One Year Warranty

The VT 5006 S13 is a part of the VT-5000 IO Cards Series by Bosch Rexroth Indramat.

### Specifications

Solenoid Resistance (output stage):	10?@20°C	Voltage Amplitude (uss):	5 V per output	Last Verified:	07/11/2025 12:25 PM
Power Consumption:	<50 VA	Regulated Voltage:	±9 V ±1% (up to ±25 mA load)	Solenoid Max Current (output stage):	2.2 A ±20%
Operating Range:	22 V to 35 V	Operating Voltage:	24 V DC (+40%/? 5%)	<b>Oscillator Frequency:</b>	2.5 kHz ±10%
Fuse Rating:	2.5 A T (slow? blow)	Max Inductive Load (transducer driver):	30 mA	Measuring Sockets (wax):	, 0 to ±6 V (Ri = 100 ?)
Front Panel Height:	3 HE (128.4 mm)	Front Panel Width (component side):	7 TE (35.56 mm)	Front Panel Width (solder side):	1 TE (5.08 mm)
Card Dimensions:	100 x 160 mm (Euro-card, DIN 41494)	Clock Frequency:	Self?clocking up to 1.5 kHz	Current Consumption:	<2 A

#### **Contact Us**

- ♀ 1620 Old Apex Road, Cary, NC 27513, USA
- 🤳 Toll Free: <u>1-888-551-3082</u>
- International: <u>1-919-443-0207</u>
- <u> Fax: 1-919-867-6204</u>
- Email: <u>sales@automation-factory.com</u>

## **Shipping Options**



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.