

#### **Bosch Rexroth Indramat - VT-5000 IO Cards**

VT-5007 S11



# <table-of-contents> In Stock, Ships Fast

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Checkout

Free Ground

One Year Warranty

The VT-5007 S11 is a part of the VT-5000 IO Cards Series by Bosch Rexroth Indramat.

## Specifications

Card Dimensions:	100 x 160 mm (Euro-card, DIN 41494)	Connector Type:	32-pin male, DIN 41612 Form D	Current Consumption	<2 A
Front Panel Height:	3 HE (128.4 mm)	Front Panel Width:	1 TE (solder) / 7 TE (component)	· Fuse Rating:	2.5 A time-delay
Measuring Socket:	0 to ±6 V; Ri = 100 ?	Operating Temperature:	0 to 50 °C	Operating Voltage:	24 VDC (+40%/ser#5%), range 22ser#35 V
Position Transducer Load:	30 mA at 5 V output	Power Consumption:	<50 VA	Ramp Time Adjustment:	30 ms to ~1 s or 5 s (±20%)
Regulated Voltage Output:	±9 V (±1%)	Self-clocking Frequency:	up to ~1.5 kHz	Solenoid Output Current:	1.8 A max (±20%)
Solenoid Output Resistance:	5.4 ? (at 20 °C)	Storage Temperature:	-25 to +85 °C	Transducer Oscillator Frequency:	2.5 kHz (±10%)
Weight:	0.15 kg	Last Verified:	07/01/2025 9:04 AM		

#### **Contact Us**

- ♀ 1620 Old Apex Road, Cary, NC 27513, USA
- J Toll Free: <u>1-888-551-3082</u>
- International: <u>1-919-443-0207</u>
- 둼 Fax: <u>1-919-867-6204</u>
- Email: <u>sales@automation-factory.com</u>

### **Shipping Options**



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.