

#### **Bosch Rexroth Indramat - VT-5000 IO Cards**





# Request a Quote

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer

Ċ
Secure Online
Checkout

Free Ground Shipping

One Year Warranty

The VT 5008S11 is a part of the VT-5000 IO Cards Series by Bosch Rexroth Indramat.

## Specifications

Card Dimensions:	100 x 160 mm (Euro-card DIN 41 494)	Clock Frequency:	Self-clocking up to 1.5 kHz	Command Input Range:	0 to ±6 V (₽°6 V=+100%, +6 V=?100%)
Connector:	32-pin male, DIN 41612 Form D	Current Consumption:	<2 A	Max Load:	30 mA
Nominal Operating Voltage:	24 VDC (+40%/-5%)	Operating Voltage Range:	22 V to 35 V	Oscillator Frequency:	2.5 kHz ±10%
Output Stage Max Current:	2.2 A ±20%	Output Stage Resistance:	10 ? (at 20°C)	Position Output Range:	0 to ±6 V, Ri = 100 ?
Power Consumption:	<50 VA	Regulated Voltage:	±9 V ±1%, max external load 25 mA	Voltage Amplitude per Output:	5 V per output
Last Verified:	07/11/2025 10:51 AM				

#### Contact Us

- ♀ 1620 Old Apex Road, Cary, NC 27513, USA
- J Toll Free: <u>1-888-551-3082</u>
- International: <u>1-919-443-0207</u>
- <u> Fax: 1-919-867-6204</u>
- Email: <u>sales@automation-factory.com</u>

### **Shipping Options**



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.