

#### **Bosch Rexroth Indramat - VT-5000 IO Cards**





# <table-of-contents> In Stock, Shipping Varies

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Checkout

colf algolving up

Free Ground

Shipping



One Year Warranty

The VT 5008S12 is a part of the VT-5000 IO Cards Series by Bosch Rexroth Indramat.

## Specifications

Card dimensions:	100 x 160 mm	Clock frequency:	to approx. 1.5 kHz	Command input 5 voltage:	0 to ± 10 V
Command inputs 1-4 voltage:	± 9 V (ref. M0)	Connector:	32-pin male (DIN 41612 Form D)	Current consumption:	< 2 A
Enable input:	active >8.5 V, inactive <6.5 V	Fuse rating:	2.5 A time-delay	Max driver load:	30 mA
Operating voltage:	24 VDC (+40% / -5%)	Oscillator frequency:	2.5 kHz ±10%	Power consumption:	< 50 VA
Ramp time adjustment:	30 ms to 5 s (±20%)	Regulated voltage:	± 9 V ±1%, Ioadable 25 mA	Relay coil resistance:	2150 ?
Relay release voltage:	2.4 V	Relay response voltage:	16.8 V	Solenoid current:	2.2 A ±20%
Solenoid resistance:	10 ? (at 20 °C)	Weight:	approx. 0.15 kg	Last Verified:	07/11/2025 10:29 AM

#### **Contact Us**

- ♀ 1620 Old Apex Road, Cary, NC 27513, USA
- J Toll Free: <u>1-888-551-3082</u>
- International: <u>1-919-443-0207</u>
- 둼 Fax: <u>1-919-867-6204</u>
- Email: <u>sales@automation-factory.com</u>

## **Shipping Options**



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.