

Bosch Rexroth Indramat - VT-5000 IO Cards

VT 5010 S22



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 5010 S22** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

Specifications

Actual Pressure Signal Output:	0...10V	Actual Swivel Angle Signal Output:	-10...+10V (-100%...+100%)	Analog Actual Pressure Input:	0...10V (or 0...5V) or 0...20mA; Rin=100?
Analog Actual Swivel Angle Input:	±10V (-100% to +100%); Rin=2k?	Analog Command Pressure Input:	0...10V; Rin >50k?	Analog Command Swivel Angle Input:	±10V (regenerative 0...10V); Rin >50k?
Current Consumption:	<2A (typ. 0.6A, peak 1.25A) 24V DC (+40%/? 10%; 21.6?	Enable Input Voltage:	>12V	Lower Limit Voltage:	22V
Operating Voltage:	33.6V)	Oscillator Amplitude (Dm2):	~3.6V (port 8a)	Oscillator Amplitude (Iw9):	~1V (port 12a/14a)
Oscillator Frequency:	~5.4kHz	Solenoid Output Current:	up to 2.5A (R20=2?)	Upper Limit Voltage:	35V
Last Verified:	07/12/2025 2:11 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

