

Bosch Rexroth Indramat - VT-5000 IO Cards

VT 5011 S44



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 5011 S44** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

Specifications

Analog pressure actual input current: 4-20 mA, RB=100 ?
Analog swivel angle command input: ±10 V, Re>50 k?

>12 V

Enable input level:
Oscillator amplitude port 8a: 3.6 V

Solenoid output current max: 2.5 A (R20=2 ?)

Swivel angle signal output: ±10 V (-100% to +100%)

Analog pressure actual input voltage: 0-10 V, Re>50 k?
Auxiliary output voltage: ±15 V ±6%, I_{max} 10 mA
24 V DC (+40%/-10%), 21.6-33.6 V

Operating voltage: ~5.4 kHz

Oscillator frequency: 21 V

Supply lower limit: 07/11/2025 3:28 PM

Last Verified:

Analog pressure command input: 0-10 V, Re>50 k?
Current consumption: max 0.6 A (peak 1.25 A)

Oscillator amplitude port 12a/14a: 1 V
Pressure signal output: 0-10 V

Supply upper limit: 35 V

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.