

## Bosch Rexroth Indramat - VT-5000 IO Cards

### VT 5012 S32



 **In Stock, Ships Today**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **VT 5012 S32** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

## Specifications

<b>Adjustment Controls:</b>	Ramp time & command via jumpers/potentiometers	<b>Analog Actual Position Output (x):</b>	0 to 6.6?V, input Ri=100??	<b>Analog Command Output (w):</b>	0 to 7.6?V, input Ri=100??
<b>Card Dimensions:</b>	100×160?mm (Euro? card, DIN?41?494)	<b>Clock Frequency:</b>	?1.5?kHz (self? clocking)	<b>Coil Resistance Range:</b>	5.4?Ω10??
<b>Connector Type:</b>	32?pin male, DIN?41? 612 form D	<b>LED Indicators:</b>	Enable (yellow), Ready (green)	<b>Operating Temp. Range:</b>	0°C to 50°C
<b>Oscillator Frequency:</b>	2.5?kHz ±10%	<b>Output Current Range:</b>	1.8?A2.2?A ±20%	<b>Panel Height:</b>	3?HE (128.4? mm)
<b>Panel Width (component side):</b>	7?TE (35.6?mm)	<b>Panel Width (solder side):</b>	1?TE (5.08?mm)	<b>Ramp Time:</b>	30?ms to 5?s (±20%)
<b>Regulated Supply:</b>	±9?V ±1%, ±25?mA ext. load	<b>Supply Voltage:</b>	24?V?DC (+40%/?5%)	<b>Warranty:</b>	1?year
<b>Weight:</b>	0.15?kg	<b>Last Verified:</b>	07/11/2025 11:17 AM		

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

## Shipping Options



## Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.