



Bosch Rexroth Indramat - VT-5000 IO Cards

VT 5025-17b



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 5025-17b** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

Specifications

Actual Pressure Input Voltage: 0/10 V (0/5, 0.5/5, 1/10 V) via 100 ?
Auxiliary Output Voltage: ±15 V (±2%/? 6%), max 10 mA
Oscillator Amplitude (Valve): 3.6 V @ port 8a
Pressure Command Input: 0/10 V, Zin >50 k?

Supply Current: 0.6 A rated, 1.25 A max

Angle Command Input: ±10 V (0/10 V regen), Zin >50 k?
Enable Input Threshold: >12 V

Oscillator Frequency: 5.4 kHz

Pressure Output: 0/10 V
24 V DC (+40%/? 10%)

Supply Voltage: 21.6V-33.6 V

Angle Output: ?10/+10 V (?100% +100%)
Oscillator Amplitude (Angle): 1 V @ ports 12a/14a

Power Limit Input: 0/10 V, Zin >50 k?
Solenoid Max Current: 2.5 A (coil R=2 ?)

Last Verified: 07/11/2025 3:44 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.