

## Bosch Rexroth Indramat - VT-5000 IO Cards

### VT 5025 S12



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **VT 5025 S12** is a part of the **VT-5000 IO Cards Series** by **Bosch Rexroth Indramat**.

### Specifications

<b>Card dimensions:</b>	Euro-card 100 x 160 mm (DIN 41 494)	<b>Clock frequency:</b>	Self-clocking up to approx. 1.5 kHz	<b>Connection type:</b>	32-pin male multipoint connector, DIN 41 612, form D
<b>Current consumption:</b>	< 2 A	<b>Front panel height:</b>	3 HE (128.4 mm)	<b>Fuse rating:</b>	2.5 A slow-blow 24 VDC (+40%/-5%)
<b>Input impedance:</b>	100 ?	<b>Max load capability:</b>	30 mA	<b>Operating voltage:</b>	30 ms to 5 s (±20%)
<b>Oscillator frequency:</b>	2.5 kHz (±10%)	<b>Power consumption:</b>	< 50 VA	<b>Ramp time adjustment range:</b>	Imax 1.8 A (±20%), R=5.4 ?
<b>Regulated output voltage:</b>	±9 V (±1%), load ±25 mA	<b>Socket input range:</b>	0 to ±6 V (±100%)	<b>Solenoid variant 1 current/resistance:</b>	07/12/2025 12:13 AM
<b>Solenoid variant 2 current/resistance:</b>	Imax 2.2 A (±20%), R=10 ?	<b>Weight:</b>	0.15 kg	<b>Last Verified:</b>	

### Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

### Shipping Options



### Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.