



Bosch Rexroth Indramat - VT Servo Amplifiers

VT 10468-3X/B0-R0



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 10468-3X/B0-R0** is a part of the **VT Servo Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Brake type:	Fraction Brakes	Cable length:	600mm	Current consumption:	Approx. 30 mA
Fuse:	2 A	Lever displacement angle:	20 degree from spring center position	Lever form:	Hand lever
Operating Force:	6N (Start value), 10N(Final Value)	Permissible ambient temperature:	-25 to +70 C	Protection to EN 60529:	IP65(Below the mounting plane)
Supply voltage:	+/-15 VDC	Weight:	1.5kg	Last Verified:	07/01/2025 4:55 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.