

Bosch Rexroth Indramat - VT Servo Amplifiers

VT 11073-10



 [Request a Quote](#)

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 11073-10** is a part of the **VT Servo Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Command input range:	±10 V differential, approx. 20 k Ω	Connection type:	12 screw terminals DIN rail TH 35 (EN 60715)	Current consumption:	approx. 1.2 A
Dimensions (W×H×D):	40×79×85.5 mm	Mounting:	21 to 35 V DC	Nominal supply voltage:	24 V DC (+40%/-10%)
Operating temperature:	0 to +50 °C	Operating voltage range:	IP20 (EN 60529)	Output current adjustment range:	10% to 100% of I _{max}
Power consumption:	25 VA	Protection rating:	1000 mA	Pulse frequency (VT11004/VT11015):	230 Hz (±15%)
Pulse frequency (VT11026):	170 to 200 Hz (±15%)	Solenoid current (VT11004/VT11015):	0.16 kg	Solenoid current (VT11026):	800 mA (R20=12 ?)
Switching output:	0 to +6 V (?10 k Ω)	Weight:		Last Verified:	06/30/2025 10:09 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.