



Bosch Rexroth Indramat - VT Servo Amplifiers

VT 11123-10



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 11123-10** is a part of the **VT Servo Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Adjustment Range - Jump Height:	0 to approx. 50% of I _{max}	Adjustment Range - Ramp Time:	approx. 50 ms to approx. 5 s	Current Consumption:	< 1.3 A
Dimensions (w X H X D):	40 mm x 79 mm x 85.5 mm	Inputs - Command Value Voltage:	0 to ±10 V, Input Impedance > 50 kΩ	Inputs - Enable:	10 V < UF1/UF2 < 35 V (active) and UF1/UF2 < 8 V (inactive)
Mounting Type:	Carrier rail TH 35, 7.5 to EN 60715	Operating Range:	21 V to 35 V	Operating Voltage:	24 VDC +40% / -10%
Outputs - Maximum Solenoid Current:	1.75 A (for 4WRA 10, Component Series 1X)	Power Consumption:	< 30 VA	Type Of Protection:	IP 20 to EN 60529
Weight:	0.16 kg	Last Verified:	08/31/2025 10:08 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.