

Bosch Rexroth Indramat - VT Servo Amplifiers

VT 17158-21



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT 17158-21** is a part of the **VT Servo Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Command Value Voltage:	0 to ± 10 V, input impedance > 50 k Ω	Connection Type:	12 screw terminals	Current Consumption:	Less than 1.3 A (typ. 1.2 A)
Dimensions:	40 x 79 x 85.5 mm (W x H x D)	Ingress Protection:	IP20 (EN 60529)	Jump Height Range:	0 to approx. 50% of I_{max}
Max Solenoid Current:	1.75 A	Mounting Type:	Carrier rail TH 35 $\times$ 7.5 (EN 60715)	Operating Temperature Range:	0 to $+50$ $^{\circ}\text{C}$
Power Consumption:	Approx. 30 VA	Ramp Time Range:	approx. 50 ms to 5 s	Rated Supply Voltage:	24 V DC $+40\%$ / -10%
Solenoid Resistance Options:	4.8, 5.4, 10, 19.5 Ω	Supply Voltage Range:	21 to 35 V	Weight:	0.16 kg
Last Verified:	07/11/2025 12:38 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.