



Bosch Rexroth Indramat - VT-SSPA Plugin Proportional Amplifiers

VT-SSPA1-1-10/V001



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT-SSPA1-1-10/V001** is a part of the **VT-SSPA Plugin Proportional Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Biasing Current (adjustment Range):	0 ... 300 mA	Biasing Current (factory Setting):	100 mA	Clock Frequency At I_{max}:	340 Hz
Command Value Input:	0 ... 10 V (proportional) and 12 V to UB (switching range)	Maximum Current (adjustment Range):	Up to 1.7 A	Minimum Coil Inductance:	15 mH
Nominal Current (factory Setting):	1.6 A	Operating Voltage:	24 V DC	Permissible Operating Temperature Range:	-25 °C to +70 °C
Ramp Time (adjustment Range):	100 ms to 5 s	Resistance:	20 k Ω	Type Of Connection (cable Gland):	4 screw terminals
Type Of Connection (m12 Component Connector):	4-pin, M12 x1	Voltage Range:	u(t) _{max} = 35 V, u(t) _{min} = 18 V	Weight:	0.125 kg
Last Verified:	08/10/2025 11:10 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.