

Bosch Rexroth Indramat - VT-SSPA Plugin Proportional Amplifiers

VT-SSPA1-508-22/V0



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT-SSPA1-508-22/V0** is a part of the **VT-SSPA Plugin Proportional Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Biasing Current Factory Setting:	100 mA	Biasing Current Range (I_b):	0 ^{SPR} 350 mA	Clock Frequency at I_{max}:	305 Hz
Connection:	4 screw terminals; cable diameter 4.5 ^{SPR} 11 mm	Maximum Cable Inductance (L_{max}):	100 µH	Maximum Current Range (I_{max}):	0 ^{SPR} 2.6 A
Minimum Coil Inductance (L_{min}):	15 mH	Nominal Current Factory Setting:	2.5 A	Operating Voltage:	24 V DC
Proportional Command Voltage Range:	0 ^{SPR} 10 V	Ramp Time High-Rate Range:	60 ms ^{SPR} 5 s	Ramp Time Standard Range:	100 ms ^{SPR} 5 s
Resistance:	20 k?	Switching Command Voltage Range:	12 ^{SPR} 35 V	Weight:	0.125 kg
Last Verified:	08/12/2025 8:44 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.