



Bosch Rexroth Indramat - VT-VRPA Electric Amplifiers

VT-VRPA1-151-11/V0/0



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT-VRPA1-151-11/V0/0** is a part of the **VT-VRPA Electric Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Additional Note:	Coils must be ordered separately	Coil Seal Kit:	Code RG16A1PMVQ0010, Material No. R934003962	100%
Electrical Voltage Type:	Direct current (DC)	Filtration:	10 µm nominal, NAS 8, ISO 4406 19/17/14	Duty Cycle:
Fluid Type:	Mineral-based or synthetic lubricants	Internal Leakage:	80 cm ³ /min at 210 bar with oil viscosity of 46 cSt	Fluid Temperature Range:
Nominal Coil Voltage:	30W -10%/+10%	Orifice:	CA-10A-3N (refer RC18325-70)	Mounting Torque:
Seal Kit Code:	RG10A3010530100, Material No. R93000990	Solenoid Type:	S7	Power Consumption:
Last Verified:	06/04/2025 12:53 PM			Viscosity Range:
				20 to 380 mm ² /s (cSt)

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

