

Bosch Rexroth Indramat - VT-VRPA Electric Amplifiers

VT-VRPA1-527-10/V0/QV



 **In Stock, Ships Fast**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT-VRPA1-527-10/V0/QV** is a part of the **VT-VRPA Electric Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Adjustable parameters:	Zero point, sensitivity	Circuit board dimensions:	100×160×?35? mm	Command value range:	0)+10?V
Feedback signal range:	0)+10?V, open-circuit protected	Interface connection:	DIN?41612 F32 connector	LED indications:	Green=Enable, Yellow=Cable break, Red=Low voltage
Max current consumption:	1.5?A (size?6), 2.5?A (size?10)	Operating temperature:	0?°C to +70?°C	PID control:	Supported for position control
Position sensing cable length:	?50?m	Power consumption:	35?W (size?6), 60?W (size?10)	Short-circuit protection:	Solenoid outputs and position sensing
Solenoid cable length:	?20?m (1.5? mm ²), 20?m (2.5? mm ²)	Solenoid current output:	2.7?A (size?6), 3.7?A (size?10)	Storage temperature:	-20?°C to +70?°C
Supply voltage (battery):	21?V to 40?V	Supply voltage (DC):	Nominal 24?V? DC	Supply voltage (rectified AC):	U _{eff} ?21?V to 28?V
Weight:	0.37?kg	Last Verified:	06/06/2025 5:25 PM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

