



Bosch Rexroth Indramat - VT-VRPA Electric Amplifiers

VT-VRPA1-537-20/V0



 **In Stock, Ships in 3-5 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **VT-VRPA1-537-20/V0** is a part of the **VT-VRPA Electric Amplifiers Series** by **Bosch Rexroth Indramat**.

Specifications

Cables For Magnets:	20...60 m (2.5 mm ² cross-section)	Control Signal Input:	0...±10 V	Error Led Indications:	Green (Enable), Yellow (Cable break), Red (Under-voltage)
Feedback Signal:	0...±10 V, Ri = 20 k?	Front Panel Compatibility:	7 TE	Mass:	0.37 kg
Output Circuit Type:	Switched mode, PID behavior	Output Current For Valve Magnet:	3.7 A max	Pcb Dimensions:	100 x 160 mm
Signal Source Potentiometer:	±10 V, 10 mA, 10 k? (or external)	Special Feature:	Cable break detection	Temperature Range (operating):	0...70°C
Temperature Range (storage):	-20...70°C	Typical Power Consumption:	55 W	Voltage Supply (ub):	21...40 V DC
Last Verified:	06/05/2025 9:29 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

