

Danaher - POWERSTAT Transformers

Q116U-3



 **In Stock, Ships in 3-5 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **Q116U-3** is a part of the **POWERSTAT Transformers Series** by **Danaher**.

Specifications

Approximate Driving Torque:	50-75 Oz-In	Connection Type:	#3 3-Phase Wye	Constant Current Load Max Ampere:	9
Constant Current Load Max Kva:	3.8 / 4.4	Constant Impedance Load Max Ampere:	12	Constant Impedance Load Max Kva:	5.0
Construction Type:	Open construction	D-c Resistance Per Coil:	0.49 Ohms	Input Frequency:	50/60 Hz
Input Voltage:	240V	Knob Rotation Cw Input Terminal:	5-5-5	Knob Rotation Cw Jumper Terminal:	4-4-4
Knob Rotation Cw Output Terminal:	3-3-3	No-load Loss At 60 Hertz:	25.5 Watts	Output Voltage:	0-240V / 0-280V
Last Verified:	09/07/2025 7:16 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.