



Danaher - POWERSTAT Transformers

Q117UM-3



Request a Quote

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **Q117UM-3** is a part of the **POWERSTAT Transformers Series** by **Danaher**.

Specifications

Connection Type:	#3 3-Phase Wye	Constant Current Load Max Amp:	10	Constant Current Load Max Kva:	4.2
Constant Impedance Load Max Amp:	13	Constant Impedance Load Max Kva:	5.4	Input Frequency:	60 Hz
Input Voltage:	240V	Knob On Radiator End Cw Jumper:	1-1-1	Knob Rotation Ccw Input Terminal:	4-4-4
Knob Rotation Ccw Jumper:	1-1-1	Knob Rotation Ccw Output Terminal:	3-3-3	Knob Rotation Cw Input Terminal:	1-1-1
Knob Rotation Cw Jumper:	4-4-4	Knob Rotation Cw Output Terminal:	3-3-3	Output Voltage:	0-240V
Last Verified:	09/06/2025 1:31 PM				

Contact Us

1620 Old Apex Road, Cary, NC 27513, USA

Toll Free: [1-888-551-3082](tel:1-888-551-3082)

International: [1-919-443-0207](tel:1-919-443-0207)

Fax: [1-919-867-6204](tel:1-919-867-6204)

Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.