



KEB - F5 Combivert Axis Drives

13.F5.G1E-3800



 [Request a Quote](#)

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **13.F5.G1E-3800** is a part of the **F5 Combivert Axis Drives Series** by KEB.

Specifications

Encoder interface:	No interface	Housing type:	E	Input identification:	3ph 400V AC/DC
Input phases:	3	Maximum braking current:	25 A	Minimum braking resistance:	16 Ohm
Overcurrent fault trip level:	43 A	Power loss at rated operation:	290 W	Rated input current:	28 A
Rated motor power:	7.5 hp / 5.5 kW	Rated output power:	9.5 kVA	Recommended wire gauge:	10 AWG
Stall current at 8 kHz:	24 A	Switching frequency:	2-16 kHz	Tightening torque:	11 in-lb
Last Verified:	05/12/2025 1:35 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.