

Kollmorgen - 5000 Indexer Drivers

PA5000



 **In Stock, Ships 2-3 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout






Free Ground
Shipping



One Year
Warranty

The **PA5000** is a part of the **5000 Indexer Drivers Series** by Kollmorgen.

Specifications

Audio Inputs:	2 × female + 2 × male Neutrik XLR-3	Bridge Power (8 ?):	1 × 5150 W	Channels:	2
Form Factor:	2U, 19" rack	Frequency Response:	<20 Hz  >20 kHz, ±1 dB	Inter-channel Crosstalk:	<-75 dBr @1 kHz, <-58 dBr @20 kHz
Net Weight:	19.5 kg	Operating Voltage:	180  250 V, 50/60 Hz	Power Consumption:	800 W
Power Output (4 ?):	2 × 2600 W	Power Output (8 ?):	2 × 1500 W	Protections:	short?circuit, no? load, mute, RF interference
Speaker Outputs:	2 × Neutrik Speakon NL4	Total Harmonic Distortion:	<0.5%, 20 Hz  20 kHz	Ventilation:	flow?through front to back
Voltage Gain:	37.87 dB	Last Verified:	05/09/2025 7:13 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.