

Sanyo Denki - BL Super Servo Amplifiers

20BA075FFW



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **20BA075FFW** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication cycle (motion):	2 ^{SFR} 16 ms	Communication cycle (robot control):	8 ^{SFR} 16 ms	Cooling method:	Passive cooling
Digital I/O:	16 inputs; 8 outputs; 19.2 ^{SFR} 30 VDC; max 0.5 A/point	Dimensions:	55×120×110 mm (W×H×D)	EtherCAT interface:	100 Mbps
Ethernet interface:	10/100/1000 Mbps (Modbus TCP, OPC?UA)	Humidity (operating/storage):	10 ^{SFR} 95% RH (non? condensing)	I/O power supply:	24 VDC (19.2 ^{SFR} 30 VDC), 20 mA
Main power supply:	24 VDC (19.2 ^{SFR} 30 VDC), 0.8 A	Mass:	300 g	Max controllable axes:	8 axes; robot control on up to 4 axes
Motion control:	Electronic cam, gear, linear & circular interpolation	Power consumption:	19.2 W	Robot control:	Supported
RS-485 interface:	9.6 ^{SFR} 115.2 kbps	Sequence control:	Supported	Storage temperature:	-40 to 70°C
USB interface:	USB 2.0	Last Verified:	06/05/2025 7:25 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

