

Sanyo Denki - BL Super Servo Amplifiers

27BA030FXT13



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **27BA030FXT13** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication Cycle:	2 to 16 ms	Control System:	Position control, Speed control, Torque control	Cooling Method:	Passive
Dimensions:	55(W) × 120(H) × 110(D) mm	Input Power Supply Voltage:	24 VDC	Installation Location:	In control panel
Mass:	300 g	Max. No. Of Controllable Axes:	8	Network Functions:	EtherCAT (100 Mbps)
Power Consumption:	19.2 W	Programming Language:	Compliance with IEC 61131-3; G-Code (SMC100-A)	Shock Resistance:	Peak acceleration 147 m/s ² for 11 ms
Storage Temperature:	-40 to 70°C	Vibration Resistance:	3.5 mm amplitude (5 to 8.4 Hz)	Last Verified:	08/21/2025 9:49 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.