

Sanyo Denki - BL Super Servo Amplifiers

27BA050FXT06



 **In Stock, Ships Today**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **27BA050FXT06** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Cooling Method:	Passive	Digital Inputs:	16 points; 24 VDC; common +/SFR input	Digital Outputs:	8 points; 19.2VDC; 0.5 A max per point; sink type EtherCAT 100 Mbps, Ethernet, RS485, USB 2.0
Dimensions (W×H×D):	55×120×110 mm	I/O Supply Voltage:	24 VDC, 20 mA	Interfaces:	
Main Power Input:	24 VDC (19.2VDC), 0.8 A	Mass:	300 g	Max Controllable Axes:	8 axes
Models:	SMC100-A, SMC100-B	Motion Control:	Electronic cam, gear, linear & circular interpolation	Operating Temperature:	0°C to 55°C
Operating/Storage Humidity:	10% to 95% non? condensing	Power Consumption:	19.2 W	Robot Control:	Cartesian, SCARA & parallel link robots
Sequence Control:	Supported	Storage Temperature:	-40°C to 70°C	Last Verified:	12/13/2025 1:55 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.