

Sanyo Denki - BL Super Servo Amplifiers

60BA050FXW0D



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **60BA050FXW0D** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Ambient Operating Temperature: 0 to 55°C

I/O Power Supply Rated Current: 20 mA

Main Power Supply Rated Current: 0.8 A

Number of Controllable Axes: Up to 8 axes

147 m/s², 11 ms (JIS B)

Shock Resistance: 3502:2011)

Last Verified: 08/22/2025 2:22 AM

Communication Cycle:

I/O Power Supply Rated Voltage: 24 VDC (19.2-30 VDC)

Main Power Supply Rated Voltage: 24 VDC (19.2-30 VDC)

Operating/Storage Humidity: 10 to 95% (non-condensing)

Storage Temperature: -40 to 70°C

Dimensions:

55 mm (W) x 120 mm (H) x 110 mm (D)

Interface:

EtherCAT 100 Mbps

Mass:

300 g


Power Consumption:

19.2 W

Vibration Resistance:

3.5 mm, 5-8.4 Hz (JIS B 3502:2011)

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.