

Sanyo Denki - BL Super Servo Amplifiers

60BB075FXW0D



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **60BB075FXW0D** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Control Functions:	Sequence control, motion control, robot control	Cooling Method:	Passive	Digital Inputs:	16 points, 24 VDC
Digital Outputs:	8 points, 19.2 VDC, 0.5 A/point	Dimensions (W×H×D):	55 mm × 120 mm × 110 mm	Humidity Range:	10 to 95% (non-condensing)
Interface:	EtherCAT (100 Mbps)	Mass:	300 g	Max Controllable Axes:	8
Power Consumption:	19.2 W	Programming Language:	IEC 61131-3 (IL, ST, LD, FBD, SFC, CFC)	Shock Resistance:	147 m/s ² , 11 ms (JIS B 3502)
Supply Voltage:	24 VDC	Supply Voltage Range:	19.2 to 30 VDC	Temperature Range:	0 to 55°C op; -40 to 70°C st
Vibration (High Freq):	10 m/s ² , 8.4 Hz (JIS B 3502)	Vibration (Low Freq):	3.5 mm, 5 Hz (JIS B 3502)	Last Verified:	08/22/2025 3:24 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

