

Sanyo Denki - BL Super Servo Amplifiers

67ZA050A84S01



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **67ZA050A84S01** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication cycle:	2 ^{SPR} 16 ms	Cooling method:	Passive	Digital I/O:	16 inputs (24 VDC), 8 outputs (19.2 ^{SPR} 30 VDC, 0.5 A)
Dimensions:	55×120×110 mm	Humidity:	10 ^{SPR} 95% non? condensing	I/O power supply:	24 VDC (19.2 ^{SPR} 30 VDC), 20 mA
Interface: EtherCAT:	100 Mbps, master	Interface: Ethernet:	10/100/1000 Mbps	Interface: RS485:	9600 ^{SPR} 115200 bps
Interface: USB:	USB 2.0	Main power supply:	24 VDC (19.2 ^{SPR} 30 VDC), 0.8 A	Mass:	300 g
Max controllable axes:	8	Operating temperature:	0 ^{SPR} 55 °C	Power consumption:	19.2 W
Shock resistance:	147 m/s ² (11 ms) per JIS B3502:2011	Storage temperature:	-40 ^{SPR} 70 °C	Vibration resistance:	3.5 mm (5 ^{SPR} 8.4 Hz) & 10 m/s ² (8.4 ^{SPR} 150 Hz) per JIS B3502:2011
Last Verified:	06/05/2025 1:54 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

