

Sanyo Denki - BL Super Servo Amplifiers 67ZA050AB22S02



 **Request a Quote**

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping




One Year
Warranty

The **67ZA050AB22S02** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication Cycle:	2 ^{SPR} 16 ms (std motion); 8 ^{SPR} 16 ms (robot)	Control Functions:	Motion control; Robot control	Controller Series:	SANMOTION C Motion Controller
Cooling Method:	Passive cooling	Digital Inputs:	16 inputs 24 VDC, common input	Digital Outputs:	8 outputs 19.2 ^{SPR} 30 VDC, 0.5 A max per point
Dimensions:	55 x 120 x 110 mm (W x H x D)	Fieldbus Interface:	EtherCAT 100 Mbps	I/O Power Supply:	24 VDC, 20 mA
Input Supply Current:	0.8 A	Input Supply Voltage:	24 VDC (19.2 ^{SPR} 30 VDC range)	Mass:	300 g
Max Controllable Axes:	8 axes	Max Operating Altitude:	2000 m	Models:	SMC100-A (high- perf); SMC100-B (standard) Electronic cam; electronic gear; linear & circular interp.
Operating Temperature:	0°C to 55°C	Power Consumption:	19.2 W	Sequence control:	
Storage Temperature:	-40°C to 70°C	Last Verified:	06/05/2025 2:14 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

