

Sanyo Denki - BL Super Servo Amplifiers

67ZA100AB53S02



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **67ZA100AB53S02** is a part of the **BL Super Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Controller Type:	SANMOTION C (Motion Controller)	Cooling Method:	Passive cooling	Digital Inputs:	16 points, 24 VDC common
Digital Outputs:	8 points, 19.2 VDC, 0.5 A max each	Dimensions:	55×120×110 mm (W×H×D)	EtherCAT Interface:	100 Mbps master
Ethernet Interface:	10/100/1000 Mbps (Modbus TCP, OPC?UA)	Mass:	300 g	Max Controllable Axes:	8 axes
Motion Control Cycle:	2 to 16 ms	Motion Control Functions:	Electronic cam, gear, linear & circular interp.	Operating Temperature:	0°C to 55°C
Power Consumption:	19.2 W	Power Supply:	24 VDC (19.2 V range); I/O 20 mA; main 0.8 A	Robot Control Cycle:	8 to 16 ms
Robot Control Functions:	Cartesian, SCARA & parallel link	RS?485 Interface:	9600 bps	Sequence Control:	Supported
USB Interface:	USB 2.0	Last Verified:	06/04/2025 5:53 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

