

Sanyo Denki - F SANMOTION Servo Amplifiers

X-PMM-0180



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **X-PMM-0180** is a part of the **F SANMOTION Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Allowable Radial Load (lbs): 18

Allowable Thrust Load (n): 20

Excitation Current (a): 0.25

Motor Mass (kg): 0.94

Power Consumption (w): 6

Last Verified: 06/04/2025
9:53 AM

Allowable Radial Load (n): 80

Brake Operating Time (ms): 20

Holding Torque (nm): 0.55

Motor Mass (lbs): 2.07

Power Supply Input (v): DC24V \pm 5%

Allowable Thrust Load (lbs): 4.5


Brake Release Time (ms): 30

Holding Torque (oz-in): 77.88

Motor Plus Brake Length: 85.8mm (3.38inch)

Rotor Inertia (oz-in²): 2.35

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.