

Sanyo Denki - P1 Super BL Servo Motors

P10B10075HXS22



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **P10B10075HXS22** is a part of the **P1 Super BL Servo Motors Series** by **Sanyo Denki**.

Specifications

Applicable Amplifier Model:	PZ0A015 or PZ0A030	Continuous Stall Armature Current:	5.2 Arms	Continuous Stall Torque:	3.9 N·m
Induced Voltage Constant:	28.5 mV/min ⁻¹	Instantaneous Maximum Stall Armature Current:	15.5 Arms	Instantaneous Maximum Stall Torque:	10.8 N·m
Maximum Rotating Speed:	3000 min ⁻¹	Operating Temperature:	0 to 40°C, 90% max humidity (non-condensing)	Phase Armature Resistance:	1.05 ?
Rated Armature Current:	5.1 Arms	Rated Output:	0.75 kW	Rated Rotating Speed:	2000 min ⁻¹
Rated Torque:	3.5 N·m	Rotor Inertia (incremental Encoder):	14.08×10 ⁻⁴ kg·m ²	Torque Constant:	0.81 N·m/Arms
Last Verified:	06/20/2025 4:22 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.