



Sanyo Denki - P3 Super BL Servo Motors

P30B06040DXS22E



 [Request a Quote](#)

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **P30B06040DXS22E** is a part of the **P3 Super BL Servo Motors Series** by **Sanyo Denki**.

Specifications

Applicable Amplifier Model:	PU0A030 / PZ0A030	Brake Holding Torque:	1.274 Nm	Brake Inertia:	$0.06 \times 10^{-3} \text{ kg} \cdot \text{m}^2$
Brake Mass:	0.44 kg	Induced Voltage Constant:	$18.6 \pm 10\% \text{ mV/min}^{-1}$	Instantaneous Maximum Stall Torque:	3.82 Nm
Maximum Rotating Speed:	4500 min ⁻¹	Operating Temperature And Humidity:	0 to 40°C, 90% RH (non-condensing)	Phase Armature Resistance:	1.4 Ω
Rated Armature Current:	2.7 Arms	Rated Output:	400 W	Rated Rotating Speed:	3000 min ⁻¹
Rated Torque:	1.274 Nm	Rotor Inertia (inc):	$0.255 \times 10^{-3} \text{ kg} \cdot \text{m}^2$	Torque Constant:	0.533 Nm/Arms
Last Verified:	08/22/2025 11:24 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.