

## Sanyo Denki - P3 Super BL Servo Motors

### XP30C06010DXS21



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **XP30C06010DXS21** is a part of the **P3 Super BL Servo Motors Series** by **Sanyo Denki**.

## Specifications

<b>Amplifier Power Supply:</b>	200 to 230 V AC, +10%/-15%, 50/60 Hz (single-phase, $\pm 3$ Hz)	<b>Brake Excitation Voltage:</b>	90 V (with 24 V in brackets indicating alternate value)	<b>Continuous Stall Torque:</b>	20.69 N·m
<b>Electric Time Constant:</b>	23.6 ms	<b>Flange Size:</b>	60 mm	<b>Instantaneous Maximum Stall Torque:</b>	21.96 N·m
<b>Mass (including Wiring-saving Inc):</b>	21.15 kg	<b>Maximum Rotating Speed:</b>	4,500 rpm	<b>Mechanical Time Constant (w/o Sensor):</b>	20.71 ms
<b>Motor Operating Temperature And Humidity:</b>	0 to 40°C, 90% or less (non-condensing) Approximately 100 W	<b>Phase Armature Resistance:</b>	20.39 $\Omega$	<b>Rated Armature Current:</b>	24.6 Arms
<b>Rated Output:</b>	07/11/2025	<b>Rated Rotating Speed:</b>	3,000 rpm	<b>Rated Torque:</b>	20.63 N·m
<b>Last Verified:</b>	1:38 AM				

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

## Shipping Options



## Payment Methods

