

Sanyo Denki - P5 Super BL Servo Motors

P50B07040DCN00



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **P50B07040DCN00** is a part of the **P5 Super BL Servo Motors Series** by **Sanyo Denki**.

Specifications

Amplifier Mass:	2.2 kg	Applicable Amplifier Model:	PU0A030-/PZ0A030-	Brake Excitation Current:	0.08 (0.3) A
Brake Excitation Voltage:	90 (24) V	Brake Holding Torque:	0.98 N?m	Induced Voltage Constant:	16.8 ± 10% mV/min? ¹
Maximum Rotating Speed:	4,500 min? ¹	Phase Armature Resistance:	1.65 ?	Rated Armature Current:	3.0 Arms
Rated Output:	400 W	Rated Power Rate:	22.1 kW/S	Rated Rotating Speed:	3,000 min? ¹
Rated Torque:	1.274 N?m	Rotor Inertia (inc):	0.74 × 10?? kg?m ² (GD ² /4)	Torque Constant:	0.481 N?m/Arms
Last Verified:	08/22/2025 6:27 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.