

Sanyo Denki - P5 Super BL Servo Motors

P50B0730VXKS7



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **P50B0730VXKS7** is a part of the **P5 Super BL Servo Motors Series** by **Sanyo Denki**.

Specifications

Amplifier Power Supply:	200 to 230V AC +10% -15% 50/60Hz ±3Hz 3-phase	Brake Excitation Current:	0.08 (0.3) A	Brake Excitation Voltage:	90 V (24)
Brake Holding Torque:	0.98 N?m	Brake Mass:	0.57 kg	Induced Voltage Constant:	16.86 ± 10%
Mass Including Wiring-saving Inc:	1.71 kg	Maximum Rotating Speed:	4500 min? ¹	Maximum Stall Torque:	2.94 N?m
Operating Temperature:	0 to 40°C	Phase Armature Resistance:	2.9 ?	Rated Output:	300 W
Rated Rotating Speed:	3000 min? ¹	Rated Torque:	0.931 N?m	Torque Constant:	0.483 N?m/Arms
Last Verified:	08/22/2025 11:29 AM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.