



Sanyo Denki - P6 Super BL Servo Motors

P60B13150BXS00



In Stock, Ships in 3-5 Days

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **P60B13150BXS00** is a part of the **P6 Super BL Servo Motors Series** by **Sanyo Denki**.

Specifications

Brake Excitation Voltage:	90 V	Continuous Stall Armature Current:	Approximately 7.0 Arms	Continuous Stall Torque:	Approximately 8.9 N·m
Electric Time Constant:	Approximately 5.8 ms	Induced Voltage Constant:	Approximately 54.9 mV/(min)	Instantaneous Maximum Stall Armature Current:	Approximately 18.2 Arms
Instantaneous Maximum Stall Torque:	Approximately 21.6 N·m	Maximum Rotating Speed:	2000 rpm	Phase Armature Resistance:	Approximately 0.9 ?
Rated Armature Current:	Approximately 6.7 Arms	Rated Output:	1.5 kW	Rated Power Rate:	Approximately 13.5 kW/S
Rated Rotating Speed:	2000 rpm	Rated Torque:	Approximately 7.0 N·m	Torque Constant:	Approximately 1.55 N·m/Arm
Last Verified:	07/09/2025 8:24 PM				

Contact Us

📍 1620 Old Apex Road, Cary, NC 27513, USA

📞 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

🌐 International: [1-919-443-0207](tel:1-919-443-0207)

📠 Fax: [1-919-867-6204](tel:1-919-867-6204)

✉ Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.