

## Sanyo Denki - P6 Super BL Servo Motors

### P60B13150HBPD3



 **In Stock, Ships Today**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **P60B13150HBPD3** is a part of the **P6 Super BL Servo Motors Series** by **Sanyo Denki**.

## Specifications

<b>Brake excitation current:</b>	0.25 A	<b>Brake excitation voltage:</b>	90 V DC	<b>Brake type:</b>	Integrated electromagnetic
<b>Continuous stall armature current:</b>	11.0 A	<b>Continuous stall torque:</b>	9.0 N·m	<b>Electrical supply:</b>	200-230 V AC, ±10%, 50/60 Hz, 3-phase
<b>Instantaneous max stall armature current:</b>	31 A	<b>Instantaneous max stall torque:</b>	31 N·m	<b>Operating ambient temperature:</b>	0°C to +40°C
<b>Protection method:</b>	IP67 enclosure, fully closed, self-cooled	<b>Rated armature current:</b>	10.5 A	<b>Rated output:</b>	1.5 kW
<b>Rated speed:</b>	3500 rpm	<b>Rated torque:</b>	7.5 N·m	<b>Torque constant (kt):</b>	0.80 N·m/A
<b>Last Verified:</b>	07/09/2025 12:17 AM				

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

## Shipping Options



## Payment Methods

