

**Sanyo Denki - P6 Super BL Servo Motors****P60B18350LXF2A** **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer

Secure Online  
CheckoutFree Ground  
ShippingOne Year  
Warranty

The **P60B18350LXF2A** is a part of the **P6 Super BL Servo Motors Series** by **Sanyo Denki**.

**Specifications**

<b>Applicable Amplifier:</b>	PZ0A300	<b>Current:</b>	24.0 A	<b>Dimensions of flange angle:</b>	180mm
<b>Induced Voltage Constant:</b>	84.3 mV/min?1	<b>Instantaneous Maximum Stall Armature Current:</b>	37.1 Arms	<b>Maximum Rotating Speed:</b>	2,000 min?1
<b>Motor Protection:</b>	IP67 Fully Closed, Self-Cooled	<b>Operating Temperature Range:</b>	0 to 40?	<b>Rated Output:</b>	3.5 kW
<b>Rated Rotating Speed:</b>	1,500 min?1	<b>Rated Voltage:</b>	AC 200 V	<b>Torque Constant:</b>	1.35 N·m/Arms
<b>Last Verified:</b>	08/22/2025 11:32 AM				

**Contact Us** 1620 Old Apex Road, Cary, NC 27513, USA Toll Free: [1-888-551-3082](tel:1-888-551-3082) International: [1-919-443-0207](tel:1-919-443-0207) Fax: [1-919-867-6204](tel:1-919-867-6204) Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)**Shipping Options****Payment Methods**

Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.