



Sanyo Denki - PQ Type M Servo Amplifiers

PQM0PA12001



In Stock, Ships in 3-5 Days

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PQM0PA12001** is a part of the **PQ Type M Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Control Circuit Voltage:	1Ø, 200 ^{SPR} 230 VAC ±10% (50/60 Hz)	Control Power Input Capacity:	200 VA (5 serv amps)	Humidity (Op/St):	~90% RH (no condensation)
Main Power Input Capacity:	20 kVA	Main Voltage 200^{SPR}230 VAC:	3Ø, 200 ^{SPR} 230 VAC ±10% (50/60 Hz)	Main Voltage 400^{SPR}460 VAC:	3Ø, 400 ^{SPR} 460 VAC ±10% (50/60 Hz)
Mass:	~5.0 kg	Min Regen Resistor R:	~5.0 ?	Operating Temp:	32°F to 131°F
Protections:	Ovltg, phase loss, regen err, overheat	Rated Output:	12 kW	Shock Resistance:	2G
Storage Temp:	-4°F to 149°F	Structural Design:	Built-in tray PSU	Vibration Resistance:	0.5G, 10 ^{SPR} 55 Hz, 2h (X/Y/Z)
Last Verified:	06/19/2025 6:39 PM				

Contact Us

📍 1620 Old Apex Road, Cary, NC 27513, USA

📞 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

🌐 International: [1-919-443-0207](tel:1-919-443-0207)

📠 Fax: [1-919-867-6204](tel:1-919-867-6204)

✉ Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.