



Sanyo Denki - PY Super BL Servo Amplifiers

PY0A030A0132S01



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A030A0132S01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Continuous Stall Armature Current:	31.6 Arms	Continuous Stall Torque:	32.0 Nm	Electrical Time Constant:	33 msec
Induced Voltage Constant:	36.7 mV/(min?1) or 36.7 V/krpm	Inertia:	58.1×10?? kg·m ² (approx.)	Instantaneous Maximum Stall Armature Current:	79.7 Arms
Instantaneous Maximum Stall Torque:	70.0 Nm	Maximum Revolution Speed:	2500 rpm	Mechanical Time Constant:	0.68 msec
Phase Armature Resistance:	0.043 ?	Rated Armature Current:	24.1 Arms	Rated Output Power:	4500 W
Rated Revolution Speed:	2000 rpm	Rated Torque:	21.5 Nm	Torque Constant:	1.05 Nm/Arms
Last Verified:	07/05/2025 11:05 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.