



Sanyo Denki - PY Super BL Servo Amplifiers

PY0A030A1N41P01



 Request a Quote

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A030A1N41P01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

| | | | | | |
|----------------------------------|--------------------|------------------------------------|------------------|--|------------|
| Applicable Load Inertia: | JM×4 kg?m2 | Continuous Stall Torque: | 3.9 N?m | Electrical Time Constant: | 3.0 msec |
| Induced Voltage Constant: | 28.5 mV/min?1 | Inertia (including Abs-r?): | 14.08×10?4 kg?m2 | Instantaneous Maximum Stall Torque: | 10.8 N?m |
| Maximum Revolution Speed: | 3000 min?1 | Mechanical Time Constant: | 6.5 msec | Phase Armature Resistance: | 1.05 ? |
| Rated Armature Current: | 5.1 Arms | Rated Output: | 750 W | Rated Revolution Speed: | 2000 min?1 |
| Rated Torque: | 3.5 N?m | Torque Constant: | 0.81 N?m/Arms | Weight (including Abs-r?): | 10.0 kg |
| Last Verified: | 07/06/2025 3:26 PM | | | | |

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.